

# **MOTOR TREND™**



**Bluetooth Speakerphone**

**MT-2000 User Manual**

**Introduction:**

Thank you for your interest at our Bluetooth car kit. This car kit is a wireless Bluetooth kit based on the Bluetooth technology that allows you to making and talking calls without touching your mobile phone.

Read this user guide carefully before using the car kit .Read also the user guide for your phone, which provides important safety and maintenance information. Keep the car kit out of reach of small children.

Bluetooth wireless technology makes it possible to connect compatible communication devices without using cables. A Bluetooth connection does not require the devices to be in line of sight, but both devices should be within 10 meters (30feet) of each other. Connections can be subject to interference from obstructions.

The car kit is compliant with Bluetooth Specification 2.0

## Get started

### Overview



1--MUTE

2--LED display

3-- MIC input

4--Multi-function Button (MFB)

5--Volume -button

6--Volume +button

7--Mini USB 5 PIN for the charging socket

8--Speaker

Before you start using the car kit, you must charge the battery and pair the car kit with a compatible mobile phone.

## **Charger**

This car kit is intended to use with the car charger that is included in the package.

## **Charge the battery**

This device has a Rechargeable Lithium Polymer Battery 3.7V, 820mAH battery.

1. Connect the car kit to the car charger. The red indicator light is displayed during charging. If charging does not start, disconnect the charger, plug it again, and retry. Charging the battery fully may take up to 2-3 hours.
2. When the battery is fully charged, the red indicator light turns off. Disconnect the car kit from the charger.

The fully charged battery has power for up to 6 hours of talking time or up to 600 hours of standby time. However, the talking and standby time may vary when used with different mobile phones, products that use a Bluetooth connection, usage settings, usage styles, and environments.

## **Switch on and off the car kit**

To switch on, Press and hold the "MFB" multi-function button until there is a tone prompt and the blue LED flashes 5 times. The car kit is now on.

To switch off, press and hold the "MFB" for 4 seconds until the red LED flashes 5 times.

## **Pair the car kit with a compatible phone**

1. make sure your car kit is switched off
2. press and hold the "MFB" until the blue and red light flashes alternately and there is a tone prompt. The car kit is now in pairing state.
3. Activate the Bluetooth feature on the phone, and set the phone to search for Bluetooth devices. See the user guide of your phone for instructions.
4. Select the car kit (MT-2000) from the list of found devices.
5. Enter the pass code "0000" to pair and connect the car kit to your phone. In some phones you may need to make the connection separately after pairing. See the user guide of your phone for details. You only need to pair the car kit with your phone once.

If the pairing is successful, the car kit's blue light will flash 3 times briefly. The car kit's name appears in the phone menu where you can view the currently paired Bluetooth devices.

## **Basic use**

### **Call handling**

To make a call, use your phone in the normal way when the car kit is connected to your phone. And the blue LED will flash during the call.

To answer a call, press the “MFB” and the blue LED will flash during the call.

To reject a call, press the “MFB” for 2 second and there is a tone prompt when there is incoming call.

To end a call, press the “MFB” one time

In standby state, press the volume + key for 2 seconds to redial last dialed telephone No. This function requires your phone supports redialing.

In standby state, press the “MFB” to start voice dialing. This function requires your mobile support voice dialing. Check the user manual of your mobile for details.

### **Adjust the volume**

Press volume+ or volume - key to increase or to decrease the volume during a call.

### **Mute**

During a call, press and hold mute button for about 2 second to mute the MIC, the same operation to withdraw from the MIC mute state.

## **LED indicator status:**

Switch on: the blue LED flash five times.

Standby state: Blue LED flashes once every 3 second,

Connecting status: Blue LED flashes once every 3 second

Making and answering a Call: Blue LED flashes

Call: Blue lights flashing fast

Low battery warning: Red LED always on

Switch off: red LED flashes five times.

Charging state: Red LED always on and it will be off after charging completed

## **Main specifications:**

- Bluetooth v2.0+EDR, ClassII
- Operating Frequency Band: 2.4GHz ~ 2.48GHz unlicensed ISM band
- Working distance : up to 10 meters
- Integrated with echo cancellation and Noise suppressor
- Built in speaker and microphone
- Battery type: Rechargeable Lithium Polymer Battery 3.7V, 820maH
- Charging time : about 2-3 hours
- Talk time : about 6 hours

- Standby time : about 600 hours
- Dimensions: 117.5x47x15.3mm
- Pack included : MT-2000 Speakerphone,Battery,Car Charger, User Manual,

### FCC Information

This device complies with Part 15 of the FCC rules.

Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received; including interference that may cause undesired operation.

### Federal Communications Commission (FCC) Statement

This Equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful

interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Warning: Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user authority to operate the equipment.

Tested to comply with FCC standard. FOR HOME OR OFFICE USE.

Warning :

This equipment complies with FCC RF radiation exposure limits set forth for an uncontrolled environment. & This device and its antenna(s) must not be co-located or conjunction with any other antenna or transmitter.